# CS31 Speakerphone Combo

CS31 is widely used in conference for more than 20 in room attendees. Many ones used at the same time or two extra microphones connected are being good choices, supported by international advanced SonicClear IV HD, coming with a loud and lifelike sound effect.

## **Feature Highlights**

- Built-in 4 one way microphone array
- Max. up to 16.5ft (5m) and 360° voice pickup range, suitable for 20 in room attendees
- International advanced SonicClear IV HD-voice processing technology
- Equipped with two extra microphones
- Up to 2 units can be cascaded
- Be full compatible with general communication system and VoIP, such as Skype, ZOOM, Microsoft, Cisco, WebEx, Avaya, etc

## **More Details**



#### Meeting for Professional Large Conference Room

Be suitable for meeting rooms of 50m<sup>2</sup> with up to 20 in room attendees



# Built-in 4 one way microphone array

Vol+

360°pick up voice range with pick up radius over 5 meters



Instant Setup Intuitive plug and play USB, WIFI



### Purify Background

With the versatility of acoustic echo cancelation, voice band equalization, intelligent microphone reverberation, etc



## Connect to two extra mic.

Two extra microphones can be connected at the same time, which enhance the pick up radius for better conference calls

skyper	Google
Nebex	😽 GoTo Meeting
zoom	🌀 chromebox

#### Various Compatibility

Works with all the most popular communication platforms



### Conference Speakerphone Combo CS31

## **Technical Parameters**

#### DIMENSIONS

#### • Height x Width x Depth:

13.78" (350mm) x 13.78" (350 mm) x 2.17" (55mm)

#### AUDIO

- Pickup Distance: 5 meters radius
- Microphone: 4 array microphones
- Microphone Frequency Response: 50Hz-22KHz
- Speaker Frequency Response: 50Hz-22KHz
- Speaker Volume: Max 90dB
- Echo Cancellation
- Noise Suppression
- Automatic Gain Control

#### SUPPORTABLE SYSTEM

 Window XP/ Window 7/ Window8/ Window10/ Mac OSX, Android

#### **NETWORK INTERFACE**

- USB: B type
- 3.5mm Audio Interface: X2
- RJ9 Extra Mic. Interface: X2
- RJ9 Dedicated Interface

#### **INSIDE THE BOX**

- Joyusing CS31 Conference Microphone
- Audio Transfer plug
- 4 Strand 3.5MM Cable
- USB Cable
- User Manual
- Power Adapter(CS31W)
- Wireless Adapter(CS31W)

#### **OPTIONAL ACCESSORIES**

- 4P4C Cable x 3pcs
- Extension Microphone
- 3 strand 3.5mm cable

## **Reference & Contrast**

#### COMPARE



CS31U Standard Model



Wireless Model

USB	•	•
Bluetooth		
2.4G Wireless		•
Line in/out	•	•
Multy-party	•	•
Extra Microphone	•	•
Battery		•
Amplify Interface	•	•



**Online Store** 



### Joyusing Technology Co., Ltd

Website: www.joyusing.com C Email: sales@joyusing.com Address: Floor 18th-19th, Building NO.20, Hai

Online Store: store.joyusing.com

Address: Floor 18th-19th, Building NO.20, Haixi Innovation Science Park, Fuzhou, Fujian 350108, China